

RPM TRANSMITTER


Model : TR-RPM1A4

ISO-9001, CE, IEC1010



PX-01 (Optional)

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-34970699
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)



LUTRON ELECTRONIC

The Art of Measurement

RPM TRANSMITTER

Model : TR-RPM1A4

| | | |
|------------------------------|--|--|
| Measure Range | <i>Range 1 :</i> 100-2,000RPM | <i>Range 2 :</i> 1,000 RPM - 20,000 RPM |
| Output | 4 - 20 mA | |
| | <i>Range 1 :</i> 100 RPM = 4.8 mA 1,000 RPM = 12 mA 2,000 RPM = 20 mA | <i>Range 2 :</i> 1,000 RPM = 4.8 mA 10,000 RPM = 12 mA 20,000 RPM = 20 mA |
| External Adjustment | ZERO VR SPAN VR | |
| Power Supply | 90 - 260 ACV 50 Hz/60 Hz | |
| Operation Temperature | 0 - 50 °C 32 - 122 °F | |
| Operation Humidity | Less than 80 %RH | |
| Accessory Included | RPM sensor is optional. | |
| Optional Accessories | Proximity sensor: PX-01 Photo sensor: PI-06 | |
| Mounting | Din rail or Wall | |
| Case | ABS plastic | |
| Others | *3 wires connection *Exciting voltage DC 12 V | |

* Appearance and specifications listed in this brochure are subject to change without notice.

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-34970699
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)