



Description

- ◆ DC to 3000 MHz frequency range
- ◆ Matching pad matches 50 Ω to 75 Ω or 75 Ω to 50 Ω circuits
- ◆ Impedance adapter converts 50 Ω to 75 Ω with < 5.7dB loss

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Technical Specifications and Characteristics

| Mode | EMP-50J75P | EMP-30I | EMP-30G | EMP-30E | EMP-30K |
|----------------|--|------------------------------------|------------------------------------|---------------------------------------|---------------------------------------|
| Insertion Loss | 6dB max | 6dB max | 6dB max | 6dB max | 6dB max |
| Input VSWR | 1.2 | 1.2 | 1.2 | 1.2 | 1.2 |
| Input power | 2W | 2W | 2W | 2W | 2W |
| Connector | BNC(J) 50 Ω – BNC(P)75 Ω | N(P) 50 Ω – F(J)75 Ω | N(J) 50 Ω – F(J)75 Ω | SMA(J) 50 Ω – F(J) 75 Ω | SMA(J) 50 Ω – F(P) 75 Ω |