

ABM LDP6000/LDP800/LAP-1000 差動式 / 主動式探棒



Item	Bandwidth	Input Voltage Range		Attenuation Ratio	Accuracy	Input R&C
		Common Mode	Differential			
LDP-6000	25MHz	±1400V	±1400V, ±1400V	1/20, 1/200	±2%	3MΩ/10pF
LDP-6000A	25MHz	±1000V	±100V, ±1000V	1/50, 1/500	±2%	3MΩ/10pF
LDP-6000B	25MHz	±700V	±70V, ±700V	1/10, 1/100	±2%	3MΩ/10pF
LDP-6001	25MHz	±700V	±70V, ±700V	1/10, 1/100	±2%	4MΩ/10pF
LDP-6002	25MHz	±1400V	±140V, ±1400V	1/20, 1/200	±2%	4MΩ/10pF
LDP-6005	25MHz	±3500V	±350V, ±3500V	1/50, 1/500	±2%	10MΩ/10pF
LDP-6105	100MHz	±700V	±70V, ±700V	1/50, 1/500	±2%	4MΩ/10pF
LDP-6110	100MHz	±1400V	±140V, ±1400V	1/100, 1/1000	±2%	4MΩ/10pF
LDP-6110A	100MHz	±2500V	±350V, ±2500V	1/100, 1/1000	±2%	4MΩ/7pF
LDP-800	800MHz	±30V	±15V	1/10	±2%	100KΩ/10pF

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)