M.M. 100 A.CO.M.

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-54151736 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw

## 3000A — NWV WW

Click here for larger image.

## 3000 Analog Display Models

3302A	0-30V/0-2A Single
3303A	0-30V/0-3A Single
3601A	0-60V/0-1A Single

- Net Weight: 9.5 lbs.
- Product Dimensions: 4.7"(W) x 6.3"(H) x WW.100Y.COM.TW 7.9"(D)

Output Voltage	Topward 3000 Analog DC Power Supply  Zero to rated voltage continuously variable with front panel
Output voitage	coarse and fine voltage knobs
Output Current	Zero to rated current continuously variable with front panel current knob
Line Regulation	CV?.01%+2mV; CC?.01%+2mA
Load Regulation	CV?.01\$+2mV; CC<10mA @ 100W;<15mA @ above 100W
Ripple & Noise	CV<0.5mVrms @ 100W; <1mVrms @ above 100W CC<1mArms @ 100W; <3mArms @ above 100W
Transient Response	<100猶 to within 0.1% of set voltage (50% to 100% load change)
Output Impedance	<2mW +2mH
Operating Range	0 to 40?C ambient temperature
Display Accuracy	3% of full scale
Overload Protection	Automatic crossover from CV to CC mode
Series Connection	Different models can be chained to increase output up to 240 Vdc
Parallel Connection	Another same model can be paralleled to increase output to 24 Amps
Power Requirement	100/120/220/240?0% Vac; 50/60Hz single phase
Accessories	Power cord; hook-up leads; instruction manual