特力材料 886-3-5753170 胜特力电子(上海) 86-21-54151736 胜特力电子(深圳) 86-755-83298787 Http://www. 100y. com. tw

Transistors

2SA1952

## High-speed Switching Transistor (-60V, -5A) 2SA1952

#### Features

- 1) High speed switching. (tf : Typ. 0.15  $\mu$ s at Ic = -3A)
- 2) Low VCE(sat). (Typ. -0.2V at Ic/IB = -3/-0.15A)
- 3) Wide SOA. (safe operating area)
- 4) Complements the 2SC5103.

#### Absolute maximum ratings (Ta = 25°C)

Parameter	Symbol	Limits	Unit
Collector-base voltage	Vсво	-100	V
Collector-emitter voltage	VCEO	-60	V
Emitter-base voltage	VEBO	-5	V
Collector current	lc	-5	A
Collector current	IC	-10	A(Pulse)
		1	W
Collector power dissipation	Pc	10	W(Tc=25°C)
Junction temperature	Tj	150	°C
Storage temperature	Tstg	-55~+150	°C


#### Packaging specifications and hre

Туре	2SA1952		
Package	CPT3		
hfe	Q		
Code	TL		
Basic ordering unit (nieces)	2500		

#### Electrical characteristics (Ta = 25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Collector-base breakdown voltage	ВУсво	-100		-	V	$Ic = -50\mu A$
Collector-emitter breakdown voltage	BVCEO	-60		-	V	Ic=-1mA
Emitter-base breakdown voltage	ВVево	-5	-	- 1	V	$I_E = -50\mu A$
Collector cutoff current	Ісво			-10	μΑ	Vcb = -100V
Emitter cutoff current	Іево	1		-10	μΑ	$V_{EB} = -5V$
Collector-emitter saturation voltage	Vce(sat)	C-U	- 12	-0.3	V	Ic/IB=-3A/-0.15A
			. = 1	-0.5	V	Ic/I <sub>B</sub> =-4A/-0.2A
Base-emitter saturation voltage	VBE(sat)		-	-1.2	V	Ic/IB=-3A/-0.15A
		(1 - )		-1.5	V	Ic/IB=-4A/-0.2A
DC current transfer ratio	hfe	120	- 7	270	-	$V_{CE} = -2V$ , $I_C = -1A$
Transition frequency	fr	= = C	80	-	MHz	Vce = -10V , Ie = 0.5A , f = 30MHz
Output capacitance	Cob	1 ÷ .	130		pF	$V_{CB} = -10V$ , $I_E = 0A$ , $f = 1MHz$
Turn-on time	ton	0 2		0.3	μs	$Ic = -3A$ , $R_L = 10\Omega$
Storage time	tstg	= 1		1.5	μs	IB1 = -IB2 = -0.15A
Fall time	tf			0.3	μs	Vcc≃-30V

### LOOX.COM.TW External dimensions (Units : mm)



# Appendix

#### Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.
  Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

ROHM