

Transistors


General purpose transistor (dual transistors)

IMZ4

●Features

- 1) Includes a 2SA1036K and a 2SC411K transistor in a SMT package.
- 2) Mounting possible with SMT3 automatic mounting machines.
- 3) Transistor elements are independent, eliminating interference.
- 4) High collector current.
 $I_C=500\text{mA}$
- 5) Mounting cost and area can be cut in half.

●Equivalent circuit



●Structure


Epitaxial planar type
NPN / PNP silicon transistor

●Absolute maximum ratings ($T_a=25^\circ\text{C}$)

Parameter	Symbol	Limits		Unit
		Tr1 (NPN)	Tr2 (PNP)	
Collector-base voltage	V_{CB0}	40	-40	V
Collector-emitter voltage	V_{CE0}	32	-32	V
Emitter-base voltage	V_{EB0}	5	-5	V
Collector current	I_C	500	-500	mA
Collector power dissipation	P_d	300 (TOTAL)		mW *
Junction temperature	T_j	150		$^\circ\text{C}$
Storage temperature	T_{stg}	-55 to +150		$^\circ\text{C}$

* 200mW per element must not be exceeded.

●External dimensions (Unit : mm)



Transistors

●Electrical characteristics (Ta=25°C)

Tr1 (NPN)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV _{CB0}	40	—	—	V	I _C =100μA
Collector-emitter breakdown voltage	BV _{CE0}	32	—	—	V	I _C =1mA
Emitter-base breakdown voltage	BV _{EB0}	5	—	—	V	I _E =100μA
Collector cutoff current	I _{CB0}	—	—	1.0	μA	V _{CB} =20V
Emitter cutoff current	I _{EB0}	—	—	1.0	μA	V _{EB} =4V
Collector-emitter saturation voltage	V _{CE(sat)}	—	—	0.6	V	I _C /I _E =500mA/50mA
DC current transfer ratio	h _{FE}	120	—	560	—	V _{CE} =3V, I _C =100mA
Transition frequency	f _r	—	250	—	MHz	V _{CE} =5V, I _E =-20mA, f=100MHz
Output capacitance	C _{ob}	—	6.5	—	pF	V _{CB} =10V, I _E =0A, f=1MHz

* Measured using pulse current.

Tr2 (PNP)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV _{CB0}	-40	—	—	V	I _C =-100μA
Collector-emitter breakdown voltage	BV _{CE0}	-32	—	—	V	I _C =-1mA
Emitter-base breakdown voltage	BV _{EB0}	-5	—	—	V	I _E =-100μA
Collector cutoff current	I _{CB0}	—	—	-1.0	μA	V _{CB} =-20V
Emitter cutoff current	I _{EB0}	—	—	-1.0	μA	V _{EB} =-4V
Collector-emitter saturation voltage	V _{CE(sat)}	—	—	-0.6	V	I _C /I _E =-300mA/-30mA
DC current transfer ratio	h _{FE} *	120	—	560	—	V _{CE} =-3V, I _C =-100mA
Transition frequency	f _r	—	200	—	MHz	V _{CE} =-5V, I _E =20mA, f=100MHz
Output capacitance	C _{ob}	—	7	—	pF	V _{CB} =-10V, I _E =0A, f=1MHz

* Measured using pulse current.

●Packaging specifications

Type	Package	Taping		
	Code	T2R	TR	T108
	Basic ordering unit (pieces)	8000	3000	3000
EMZ1	○	—	—	—
UMZ1N	—	○	—	—
IMZ1A	—	—	—	○

Transistors

●Electrical characteristic curves

Tr1 (NPN)




Fig.1 Grounded emitter propagation characteristics




Fig.2 Grounded emitter output characteristics (I)




Fig.3 Grounded emitter output characteristics (II)




Fig.4 Collector-emitter saturation voltage vs. collector current




Fig.5 DC current gain vs. collector current




Fig.6 Gain bandwidth product vs. emitter current




Fig.7 Collector output capacitance vs. collector-base voltage
 Emitter input capacitance vs. emitter-base voltage

Transistors

Tr2 (PNP)




Fig.8 Grounded emitter propagation characteristics




Fig.9 Grounded emitter output characteristics (I)




Fig.10 Grounded emitter output characteristics (II)




Fig.11 DC current gain vs. collector current (I)




Fig.12 DC current gain vs. collector current (II)




Fig.13 Collector-emitter saturation voltage vs. collector current (I)




Fig.14 Collector-emitter saturation voltage vs. collector current (I)




Fig.15 Gain bandwidth product vs. emitter current




Fig.16 Collector output capacitance vs. collector-base voltage
 Emitter input capacitance vs. emitter-base voltage

Appendix

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.