

T-39-31

2.6 IGBT Module Range with Soft and Fast (SFD) Free-Wheeling Diodes

In order to maintain switching losses to minimal, improving Free Wheeling Diodes, (FWD), is essential and Hitachi's version of this is the Soft and Fast Recovery (SFD) Free Wheeling Diode. Basically, improvements have been achieved in the following key requirements.

- High speed ... small recovery time, t_r
- Low loss ... small reverse-peak current, I_{rp}
- Low noise ... small rate of charge of recovery current, di/dt

Ultimately reducing your energy losses, Q_{rr} .

2.7 IGBT Modules Electrical Characteristics

Voltage Series	Type Number	Absolute Maximum Ratings					Typical Electrical Characteristics							
		Package	V _{CES} (V)	V _{GES} (V)	I _C (A)	P _C (W)	V _{CE(sat)} (V)	C _{ies} (pF)	t _r (μs)	t _{on} (μs)	t _f (μs)	t _{off} (μs)	t _{rr} (μs)	
600V	MBN200A6	Single Arm	600	± 20	300	1200	2.5	18000	0.35	0.45	0.3	0.85	0.3	
	MBN400A6				400	1300								0.35
	MBM50A6	Single Phase (Dual Pack)	600	± 20	50	250	3	2400	0.3	0.35	0.3	0.55	0.1	
	MBM75A6				75	325		3700					0.15	
	MBM100A6				100	400		4500					0.15	
	MBM150A6				150	600		7400					0.4	0.7
	MBM200A6				200	730		9000					0.45	0.85
	MBM300A6				300	1000		17000					0.35	0.85
	MBB50A6				Three Phase (Six Pack)	600		± 20					50	250
	MBB75A6	75	300	3700			0.15							
MBB100A6	100	400	4500	0.15										
1200V	MBN200F12	Single Arm	1200	± 20	200	1200	3	19000	0.4	0.5	0.4	1	0.3	
	MBN300F12				300	1700		33000						
	MBM50F12	Single Phase (Dual Pack)	1200	± 20	50	400	3	4800	0.4	0.5	0.4	1	0.25	
	MBM75F12				75	700		8900					0.3	
	MBM100F12				100	800		9300					0.3	
	MBM150F12				150	800		18000					0.3	
	MBB50F12	Three Phase (Six Pack)	1200	± 20	50	-	-	-	-	-	-	-	-	

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)