mini DCA/ACA CLAMP

Model: CM-9940 *ISO-9001, CE, IEC1010*







FEATURES

- * Design meet IEC 1010 CATIII 600V safety requirment.
- * 4000 counts, Auto range & multi-functions.
- * Measurement for ACA, DCA, ACV, DCV, Ohms, Diode, Hz, Continuity beeper.
- * Water resistance for the front panel.
- * Data hold.
- * Wide ranges (600 A, 400 A) clamp on current measurement both for ACA & DCA.
- * Overload protection circuit is provided for all range.
- * LSI circuit provides high reliability and durability.
- * Pocket & slim housing case, easy carryout. Compact & heavy duty ABS housing case. and durability.

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-34970699 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw

The Art of Measurement

mini DCA /ACA CLAMP METER, Model: CM-9940

FEATURES				
* Design meet IEC 1010 CATIII 600V safety requirment.	* Wide ranges (600 A, 400 A) clamp on current			
* 4000 counts, Auto range & multi-functions.	measurement both for ACA & DCA.			
* Measurement for ACA, DCA, ACV, DCV, Ohms,	* Overload protection circuit is provided for all range.			
Diode, Hz, Continuity beeper.	* LSI circuit provides high reliability and durability.			
* Water resistance for the front panel.	* Pocket & slim housing case, easy carryout.			
* Data hold.	* Compact & heavy duty ABS housing case.			

	GENERAL SPEC	CIFICATIONS		
Display	10.8 mm (0.43") LCD, 4 digits, Max. indication 5000.	Operating Humidity	Less than 80% RH.	
Measurement	ACA, DCA, ACV, DCV, Ohms, Diode,	Weight	230 g/0.50 LB (including battery).	
Range Polarity	Hz, Continuity beeper, Relative. Automatic Switching, " - " indicates	Dimension	HWD: 178 x 64 x 33 mm (7.0 x 2.5 x 1.3 inch)	
Current Sensor	negative polarity. Hall effect sensor.	Max. Jaw Open Size	30 mm (1.18 inch) Dia.	
Zero adjustment	DCA: Push bottom adjustment. Other ranges: Automatic adjustment.	Accessories Included	Operation manual	
Over-input	Indication of " 1 " or " -1 ". Optional		Carrying case, Temperature Adapter,	
Sampling Time	Approx. 0.35 second.	Accessories &	Light Adapter, Anemometer Adapter,	
Battery	2 x 1.5V AA (UM-3) batteries.	Adapters	Pressure Adapter, RH Adapter, Tachometer Adapter, High Voltage Probe.	
Operating Temperature	0 $^{\circ}$ C to 50 $^{\circ}$ C (32 $^{\circ}$ F to 122 $^{\circ}$ F).	Y.COM.TW		

Function	Range	Resolution	Accuracy	Overload
DC/AC Voltage	400 mV (DC only)	0.1 mV	± (0.5 % + 2d)	WWW.100X.COM.T
	4 V	0.001V	DCV:	AC/DC 600 V.
	40 V	0.01V	± (1% + 2d)	WW 1007.
	400 V	0.1 V	ACV:	WWW. COX.CO
	600 V	1 V	± (1.2 % + 5d)	TWW.Ioo CON
DC /AC	400 A	0.1 A	± (2% + 5d)	W.100 2 CO
current	ACA : 0.5 to 400A	COM.TW	WWW.100X.COM.T	AC/DC 600 A
	600 A	1 A	± (2% + 8d)	TW WWW.100Y.C
Remark	24 1		range is 10 Mega ohm.	M.TW WWW.100

Remark	* Input impo * ACA, ACV	COMITY WWW.10	WWW.100Y		
Function	Range	Resolution	Accuracy	Overload	
Ohms	400 ohm	0.1 ohm	N WWW.	Y.CO. TW WY	. (

Function	Range	Resolution	Accuracy	Overload
Ohms	400 ohm	0.1 ohm	MMM. OUX.C	1007.
	4 K ohm	1 ohm	WWW.Ioo	COM.
	40 K ohm	10 ohm	± (1% + 5d)	AC / DC 400 V
	400 K ohm	100 ohm	N NN 100X	
	4 M ohm	1 K ohm	± (2% + 2d)	V.COM WWW.
	40 M ohm	10Kohm	± (3.5 % + 5d)	COM.
Frequency (5 V)	5 Hz	0.001 Hz	IN 10	Or. OW.I.A.
	50 Hz	0.01 Hz	THE WAY	AC / DC 250 V
	500 Hz	0.1 Hz	WWW.	
	5 KHz	1 Hz	± (1 % + 5 d)	
	50 KHz	0.01 KHz	WI De-	
	500 KHz	0.1 KHz		
Diode	Short/non conductance, good/defect test.			
Continuity	If measuring resistance is less than 10 ohm, the beeper will sound .			

^{*} Appearance and specifications listed in this brochure are subject to change without notice.

0310-CM9940A

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-34970699 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw