



Dual Display Digital Multimeter w/USB Connector

- With large LCD panel to make the reading clear and operation convenient.
- 4 digits multi-meter, provides high solution and high accuracy digital displaying driver.
- With RS232 interface allows user easy to connect to computer.
- It is an excellent tool for lab, factory, maintenance and repair users.

Counter	5999
Digits	3 5/6
Panel size	70×50mm, 33mm high figure
Backlight	N
Analog bargraph	Y
Auto/Manual ranging	Both
DC (V)	600mV/6V/60V/600V ±(0.5%+4d)
	1000V ±(1.0%+6d)

AC(V)	6/60/600V ±(0.8%+10d)
	750V ±(1.0%+10d)
DC(A)	600μA/6000μA ±(1.0%+10d)
	60/600mA ±(1.0%+10d)
	6A/10A ±(1.2%+10d)
AC(A)	600μA/6000μA ±(1.5%+10d)
	60/600mA ±(1.5%+10d)
	6A/10A ±(2.0%+15d)
Resistance(Ω)	600Ω ±(0.8%+5d)
	6/60/600K/6MΩ ±(0.8%+4d)
	60MΩ ±(1.2%+10d)

Frequency(Hz)	100/1000Hz ±(0.5%+4d)
	10K/100KHz ±(0.5%+4d)
	1M/20MHz ±(0.5%+4d)
Capacitance(μF)	40nF±(5%+30d)
	400nF/4μF/40μF±(3.5%+8d)
	200μF±(5.0%+10d)

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Temperature(C)	(-20C~400C) ±1.0+50d
	(400C~1000C) ±1.5+15d
Temperature (F)	(0F~750F) ±(1.0+5d)
	(750F~1832F) ±(1.5+5d)
Continuity with beeper	Y
Diode test	Y
Transistor test	Y
Display hold	Y
USB/RS232 interface	RS232
Automatic power off	Y
Low battery indication	Y
EN61010-1 CAT II /CAT III	1000VDC/750VAC
Battery	1.5V AAA×2

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-34970699
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)