

Digital Light Meter(DL-201/202)

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

H

- **DL-201 & DL-202** Digital Lux/Fc Light Meter is designed and built for use in pollution degree 2 according to JISC 1609:1993 and CNS 5119 general A class

◇ DISPLAY

- 3 1/2 digits LCD with maximum reading 1999.
- Overload indication: LCD will show "OL" in the left highest position.
- Low Battery Indication: Replace battery immediately when LCD display shows "LO".



◇ FUNCTIONS

- Low cost highest precision.
- Measuring intensities of illumination in Lux or Footcandles.
- Measuring lights source include all visible.
- Length of wiring for light sensor: approximately 1.5M.
- Cosine angular corrected.
- Operation altitude: up to 2000M.
- Many applications include: warehouses, factories, office building, schools, library, hospitals, photographic, many video, parking galleries, stadiums, building security.

◇ SAMPLING SPEED

- Sampling rate: 2.5 times per second for digital display

◇ ACCESSORIES

- Instruction manual
- Carrying case
- 9V Battery x 1 pc
- 3 ϕ plug (DL-202)

◇ POWER SUPPLY

- Battery type : 9V NEDA 1604, IEC 6F22, JIS 006P x 1 pc
- Battery life : about 200 hours

◇ OPERATION CONDITION

- Operating Temperature & Humidity: -10°C ~ 40°C, 0%~ 80%RH.
- Storage Temperature & Humidity: -10°C ~ 50°C, 0%~ 70%RH.

◇ DIMENSION

- Meter size : 130x55x38mm (LxWxH)
- Sensor size: 125x66x35mm (LxWxH)
- Weight : about 250g (including battery)