

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-54151736 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw


DS9092 <u>i</u>Button Probe

www.dalsemi.com


FEATURES

- Simple, low-cost metal stampings form a read/write probe for the <u>iButton®</u> family
- Probe guides the entry of the <u>iButton</u>
- <u>i</u>Button slides over the surface to self-clean contacts
- Accessible shallow probe cavity simplifies removal of debris such as mud
- Flexible design supports panel mount or hand-grip mount with optional tactile feedback
- Bright tarnish-resistant metal surface provides millions of operations
- Panel-mount probe, pre-wired for easy installation
- Hand-grip probe mates to RJ-11 jack for quick installation
- DS9092 probes both F3 and F5 cans. Extra consideration is required for operation with the F3 can. The attachment method of the F3 can must not interfere with the cavity dimensions of the probe, otherwise the data signal will not make contact.

ORDERING INFORMATION



PACKAGE DESCRIPTION



DESCRIPTION

The DS9092 <u>i</u>Button Probe provides the electrical contact necessary for the transfer of data to and from the DS19xx family of <u>i</u>Buttons. The round probe shape provides a self-aligning interface that readily matches the circular rim of the <u>i</u>Button's MicroCan package. Metal contacts resist wear and are easy to keep clean.

The DS9092 is available with a flat faceplate (standard) or with optional tactile feedback. The center contact of the standard reader has no moving parts, making this a more rugged interface for harsh


environments. This type of probe is best suited for designs where the <u>i</u>Button is brought into contact with the reader.

The tactile feedback probe is ideal for situations where the <u>i</u>Button is stationary and the movable reader is brought in contact with it.


Both types of probes are available in a panel-mount version. The tactile feedback probe is also available in a grip-mount version. The panel-mount probes are fastened behind the panel with a push-on type spring nut.

The two 15 cm 22AWG wires are provided for easy connection to the system microcontroller. The handgrip mount probe comes attached to a 10 cm handle and 1-meter cable which is terminated with an RJ11 jack.

STANDARD PROBE Figure 1



OPTIONAL TACTILE FEEDBACK Figure 2



2 of 2