

GPD-3303S



USB

FEATURES

- * Three Independent Output: 30V/3A x 2, 2.5V/3.3V/5V/3A x 1
- * 4 LED Display Sets : 3 Digits After Decimal Point
- * Minimum Resolution: 1mV/1mA
- * Digital Panel Control (Rotary Encoder Switch, Rubber Key With Indicator)
- * User-Friendly Operation, Coarse/Fine Volume Control
- * 4 Panel Settings Save/Recall (Plus Factory Settings Recall)
- * Key-Lock
- * Warning Buzzer
- * Output ON/OFF
- * Tracking Series and Parallel Mode
- * Smart Cooling Fan Achieving Low Noise
- * Light-Weight and Compact Design

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-54151736 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw As always the leading power supply producer in its kind, GW Instek has insisted upon the tough quality assurance policy in order to maintain its quality differential advantage. The digitally controlled GPD-3303S DC power supply are one of the latest offerings from GW Instek. It offers digital panel control, large display, bright LED indicators, high output resolution, 4 sets of setup memory, USB remote control and smart cooling fan control. Additionally, the GPD-3303S provide easy operation, a quick selection of panel settings and most importantly, a reasonable price. All these features make the GPD-3303S the most promising new comer in the power supply market.

With 1mV/1mA high resolution, the GPD-3303S, guarantees clean and stable output. You can easily simulate the device under test's accurate behavior against small changes in voltage or current, which is impossible when using a low-resolution power supply. Overall, the resolution offered by the GPD-3303S is 10 to 100 times higher than that of traditional power supply.

The GPD-3303S can save and recall panel settings, a feature which is usually not offered by general power supplies. You can quickly select a panel setting from 4 memory sets without manual configuration. Besides, the USB device port in the GPD-3303S allows you to remotely control the power supply according to your application needs.

SPECIFICATIONS	
OUTPUT	
Voltage Current	0-30.0V x 2 , 2.5V/3.3V/5.0V x 1 0-3.0A x 2 , 3.0A (fixed)
CONSTANT VOLTAGE OPERATION	N S S S S S S S S S S S S S S S S S S S
Regulation Ripple & Noise	Line regulation ≤ 0.01%+3mV Load regulation ≤ 0.01%+3mV(rating current≤ 3A) ≤ 0.02%+5mV(rating current >3A) ≤ 1mVrms (5Hz~1MHz)
Recovery Time Temp.Coefficient Output Range	\leq 100 μ S (50%Load change, Minimum load 0.5A) \leq 300ppm / $^{\circ}$ C 0 to rating voltage continuously adjustable
CONSTANT CURRENT OPERATION	N
Regulation Ripple Current Output Range	Line regulation ≤ 0.2%+3mA Load regulation ≤ 0.2%+3mA ≤3mArms 0 to rating current continuously adjustable
TRACKING OPERATION	
Regulation of PAR.	Line regulation $\leq 0.01\%+3$ mV Load regulation $\leq 0.01\%+3$ mV (rating current ≤ 3 A) $\leq 0.02\%+5$ mV (rating current > 3 A)
Regulation of SER.	Line regulation ≤ 0.01%+5mV Load regulation ≤ 300mV Tracking error ≤ 0.5%±10mV (10 ~ 30V no load) with load add load regulation ≤ 300mV) ≤ 0.5%±30mV (0 ~ 9.99V no load) with load add load regulation ≤ 300mV)
METER	
Display Resolution	4 3/4 digital 0.4" LED Display Voltage : 1mV Current : 1mA
Programm accuracy(25±5°℃) Readback accuracy(25±5°℃)	Voltage : \pm (0.03% of RDG +10 digits) Current : \pm (0.3% of RDG +10 digits) Voltage : \pm (0.03% of RDG +10 digits)
	Current : ±(0.3% of RDG +10 digits)
CH3 SPEC.	
Output Voltage Output Current Regulation(25±5°C) Repple & Noise	±2.5V/3.3V/5V±8% 3A Line regulation ≤5mV Load regulation≤15mV <2mVrms
KEY LOCK	- ('U') - x1
Yes MEMERY SAVE (DECALL	
MEMERY SAVE/RECALL	1. I recume memory before turn off
POWER SOURCE	+ 1 resume memory before turn off)
AC100V/120V/220V/230V±10%, 50	0/60Hz
DIMENSION & WEIGHT 210(W) x 130(H) x 265(D) mm ; Ap	prox. 7kg



GPD-3303S

Rear Panel



ORDERING INFORMATION

GPD-3303S Multiple Output Linear D.C. Power Supply

ACCESSORIES : User Manual x 1 Power cord x 1

Test lead GTL-104 x 2, GTL-105 x 1

Optional Accessories

GTL-242 USB Cable

勝 特 力 材 料 886-3-5753170 胜特力电子(上海) 86-21-54151736 胜特力电子(深圳) 86-755-83298787 Http://www.100y.com.tw

D14