

LDP-6000 系列差動式探棒



LDP-6001

特性：

可搭配於任何品牌示波器之使用
應用於高壓、浮地及電源的量測

勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

型號	頻寬	輸入電壓範圍		衰減倍數	精確度	輸入電阻&電容
		共模	差模			
適用於電力量測						
LDP-6001	25MHz	±700V	±70V, ±700V	1/10, 1/100	±2%	4MO//5.5pF
LDP-6002	25MHz	±1400V	±140V, ±1400V	1/20, 1/200	±2%	4MO//5.5pF
LDP-6100	100MHz	±200V	±7V, ±70V	1/1, 1/10	±2%	4MO//7pF
LDP-6101	100MHz	±700V	±70V, ±700V	1/10, 1/100	±2%	4MO//7pF
LDP-6102	100MHz	±1400V	±140V, ±1400V	1/20, 1/200	±2%	4MO//7pF
LDP-6105	100MHz	±700V	±70V, ±700V	1/50, 1/500	±2%	4MO//7pF
LDP-6110	100MHz	±1400V	±140V, ±1400V	1/10, 1/100	±2%	4MO//7pF
適用於高壓電力量測						
LDP-6005	25MHz	±3500V	±350V, ±3500V	1/50, 1/500	±2%	10MO//10pF
LDP-6010	70MHz	±7000V	±700V, ±7000V	1/100, 1/1000	±2%	10MO//10pF
LDP-6020	70MHz	±7000V	±1400V, ±14000V	1/200, 1/2000	±2%	10MO//10pF
LDP-6110A	100MHz	±2500V	±350V, ±2500V	1/100, 1/1000	±2%	4MO//7pF