

General purpose amplification (−30V, −1A)

2SB1710


●Application

Low frequency amplifier
Driver

●Features

- 1) A collector current is large.
- 2) Collector saturation voltage is low.
 $V_{CE(sat)} \leq -350\text{mV}$
at $I_C = -500\text{mA}$ / $I_B = -25\text{mA}$

●External dimensions (Unit : mm)



●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Collector-base voltage	V_{CBO}	−30	V
Collector-emitter voltage	V_{CEO}	−30	V
Emitter-base voltage	V_{EBO}	−6	V
Collector current	I_C	−1	A
	I_{CP}	−2	A*1
Power dissipation	P_C	500	mW*2
Junction temperature	T_J	150	°C
Range of storage temperature	T_{stg}	−55~+150	°C

*1 Single pulse, $P_W=1\text{ms}$

*2 Each Terminal Mounted on a Recommended

●Packaging specifications

Type	Package	Taping
	Code	TL
2SB1710	Basic ordering unit (pieces)	3000
		○

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	−30	—	—	V	$I_C=-10\mu\text{A}$
Collector-emitter breakdown voltage	BV_{CEO}	−30	—	—	V	$I_C=-1\text{mA}$
Emitter-base breakdown voltage	BV_{EBO}	−6	—	—	V	$I_E=-10\mu\text{A}$
Collector cutoff current	I_{CBO}	—	—	−100	nA	$V_{CB}=-30\text{V}$
Emitter cutoff current	I_{EBO}	—	—	−100	nA	$V_{EB}=-6\text{V}$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	−150	−350	mV	$I_C=-500\text{mA}$, $I_B=-25\text{mA}$
DC current gain	h_{FE}	270	—	680	—	$V_{CE}=-2\text{V}$, $I_C=-100\text{mA}$ *
Transition frequency	f_T	—	320	—	MHz	$V_{CE}=-2\text{V}$, $I_E=100\text{mA}$, $f=100\text{MHz}$ *
Corrector output capacitance	C_{ob}	—	7	—	pF	$V_{CB}=-10\text{V}$, $I_E=0\text{A}$, $f=1\text{MHz}$

* Pulsed

Transistors

●Electrical characteristic curves








Fig.1 DC current gain
vs. collector currentFig.2 Collector-emitter saturation voltage
base-emitter saturation voltage
vs. collector currentFig.3 Collector-emitter saturation voltage
vs. collector currentFig.4 Grounded emitter propagation
characteristicsFig.5 Gain bandwidth product
vs. emitter current

Fig.6 Switching time

Fig.7 Collector output capacitance
vs. collector-base voltage
Emitter input capacitance
vs. emitter-base voltage

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.