



勝特力材料 886-3-5753170  
勝特力电子(上海) 86-21-54151736  
勝特力电子(深圳) 86-755-83298787  
[Http://www.100y.com.tw](http://www.100y.com.tw)

1, 2, 3, 3<sup>m</sup>/m 三種夾頭, 使用靈活方便  
18000RPM, 人體力學機身, 好握好操作!

#### FEATURES:

- Up to 6 ON and OFF programming
- LCD display with large digit
- Real time display with seconds
- One minute minimum setting interval
- Reset/Recall functions
- Weekday/weekend or and day setting
- Built-in rechargeable battery
- 24 HR or AM/PM system option
- ON/AUTO/OFF over lap
- Compact terminal block easy to connect for field wiring
- LCD backlight option
- Precision time
- LED ON/OFF indicator

#### APPLICATION:

- Combined with Radio it can work as an alarm clock.
- Turn Lights ON and OFF automatically at home to prevent theft and breaking in.
- Use it to save energy by turning automatically on heaters, airconditioners, coffee makers, commercial signs, washing machines and water sprinklers at any time you select.
- Can be used with industrial equipments

#### SPECIFICATION:

- Input-----AC 100-240V (50/60Hz)
- Output-----20A for resistive load or 10A for lighting load
- Time accuracy-----±5 minutes/year
- Resistive  
Maximum-----2000W (20Ax100V AC)  
4800W (20Ax240V AC)
- Lighting Maximum-----1000W (10Ax100V AC)  
2400W (10Ax240V AC)
- Motor Maximum-----1 1/2 HP
- Memory backup-----Builtin rechargeable battery
- Dimension-----150(L)x95(W)x41(T)mm
- Color-----blue (W Backlight)  
Gray (W/O Backlight)