

Topward 1320 Digital Multimeter

勝特力材料 886-3-5753170
胜特力电子(上海) 86-21-54151736
胜特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)



DC VOLTAGE MEASUREMENT	
Range	±99.9mV, ±.999V, ±9.99V, ±99.9V, ±200V, 5 Ranges
Accuracy	±0.1% + 1d)
Input Impedance	10MW
AC VOLTAGE MEASUREMENT (AC or AC + DC TrueRMS)	
Range	±99.9mV, ±.999V, ±9.99V, ±99.9V, ±000V, 5 Ranges
Accuracy	199.9mV ~ 199.9V 4 Ranges 45Hz~ 2KHz ±0.5%+1d), 2KHz~ 10KHz ±1%+1d), 10KHz~ 20KHz ±(2%+1d), 20KHz~ 50KHz~ 50KHz ±(5%+2d), 1000V Range 45Hz-1KHz ±0.5%+2d)
Input Impedance	10MW // 100Pf
DC CURRENT MEASUREMENT	
Range	±99.9mA, ±.999mA, ±9.99mA, ±99.9mA, ±999mA, ±9.99A, 6 Ranges
Accuracy	199.9mA ~ 199.9mA 4 Ranges ±0.2%+1d), 1999mA ~ 19.99A 2 Ranges ±(0.3%+1d),
Protection	2A 250V DC or RMS [Fuse Protected] for 199.9mA ~ 1999mA
AC CURRENT MEASUREMENT (AC or AC+DC TrueRMS)	
Range	199.9mA, 1.999mA, 19.99mA, 199.9mA, 1999mA, 19.99A, 6 Ranges
Accuracy	199.9mV ~ 199.9mA 4 Ranges 45Hz~ 2KHz ±0.5%+1d), 2KHz~ 10KHz ±1%+1d), 10KHz~ 20KHz ±(2%+1d), 1999mA ~ 19.99A 2 Range 45Hz~ 2KHz ±0.5%+1d)
Protection	2A 250V DC or RMS [Fuse Protected] for 199.9mA ~ 1999mA
OHM MEASUREMENT	
Range	199.9Ohm , 1.999KOhm, 19.99KOhm 199.9KOhm , 1.999MOhm , 19.99MOhm , 6 Ranges
Accuracy	199.9Ohm range ±0.1% +1d)

	1.999KOhm ~ 1.999MOhm 4 Ranges $\pm(0.1\% +1d)$ 19.99MOhm Range $\pm(0.25\% +2d)$
DIODE TEST	YES
GENERAL	
Display	0.5", 3 1/2 Digits Green LED Display
Power Source	ACV 115V/230V, $\pm 0\%$, 60Hz/50Hz
Dimension	10.3"(W) x 3.3"(H) x 10.2"(D)
Gross Weight	3.3 lbs
Accessories	ACS-0.18 x 1, Operation Manual x 1

勝特力材料 886-3-5753170
 胜特力电子(上海) 86-21-54151736
 胜特力电子(深圳) 86-755-83298787

[Http://www.100y.com.tw](http://www.100y.com.tw)