

勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

DPS-6010 60V/10A 直流電源供應器

產品特色

- 採用PWM控制技術
- 體積小，重量輕
- 定電壓及定電流操作，CV/CC自動切換
- 具有電壓、電流粗調和微調旋鈕
- 具有多重保護功能：OVP、OCP、OTP、OPP
- 智慧風扇控制
- 可接受訂製



一般規格

| | |
|-----------------------|--|
| 型 號 | DPS-6010 |
| 輸出電壓 | 0~60V |
| 輸出電流 | 0~10A |
| Output | |
| Output voltage | DC 0~100% full range adjustable |
| Output current | DC 0~100% full range adjustable |
| OVP range | DC 0~100% of rated output |
| OCP range | DC 0~100% of rated output |
| Line regulation | CV≤0.2% + 2d CC≤0.5% + 2d |
| Load regulation | ≤0.5% + 2d |
| Ripple & Noise | ≤1% RMS |
| Display | |
| Meter | 3 3/4 digits LED display |
| Voltage resolution | 100mV |
| Current resolution | 10mA |
| Accuracy | ±1% ±1d |
| General | |
| Protection | Over Voltage Protection (OVP), Over Current Protection (OCP), Over Temperature Protection (OTP), Over Power Protection (OPP) |
| Power source | AC110V or 220V±10%, 50/60Hz |
| Input module | Power socket or terminal block |
| Operating environment | 0°C~40°C, <80%RH |
| Storage environment | -10°C~70°C, <80%RH |
| Dimension | 200x150x280mm |
| Weight | 3.2kg |