Ø16 M6 SWITCHES SERIES ILLUMINATED PUSHBUTTONS PUSHBUTTONS

勝 特 力 材 料 886-3-5753170
胜特力电子(上海) 86-21-34970699
胜特力电子(深圳) 86-755-83298787
Http://www.100y.com.tw

Popular !

TYPE NO

• Illuminated Pushbuttons

M6 P – □ □ □ □ – □ □

Ø16mm Series code ← M6 P → Pushbutton

1 2 3 4 5 6

• Pushbuttons

M6 P – □ □ □ □ – □

1 2 3 4 6

• 1 Shape

Shape	Code
Round	A
Square	B
Rectangular	C

• 2 Operation

Operation	Code
Momentary	M
Alternate	A

• 3 Terminal Style

Terminal	Code
Solder/Plug-in	S
PC board	P

• 4 Contact

Contact	Code
1C	1
2C	2

• 5 Lamp

Incandesent (AC/DC)		Neon (AC)		LED(DC)	
V	Code	V	Code	V	Code
6V	06	110V	110	6V	06E
14V	14	220V	220	12V	12E
28V	28	*	*	24V	24E

• Neon lamp color : Red (R) Green (G)
• LED lamp color : Red (R) Green (G) Yellow (Y)
White (W) Blue (B)

• 6 Lens Color

Color	Code
Red	G
Green	R
Yellow	Y
Orange	O
White	W
Blue	B

Shape	Operation	Contact	Type No. (Illuminated Pushbuttons)	Type No. (Pushbuttons)
Ø18	Momentary	1C	M6P-AMS1-□□	M6P-AMS1-□
		2C	M6P-AMS2-□□	M6P-AMS2-□
	Alternate	1C	M6P-AAS1-□□	M6P-AAS1-□
		2C	M6P-AAS2-□□	M6P-AAS2-□
18x18	Momentary	1C	M6P-BMS1-□□	M6P-BMS1-□
		2C	M6P-BMS2-□□	M6P-BMS2-□
	Alternate	1C	M6P-BAS1-□□	M6P-BAS1-□
		2C	M6P-BAS2-□□	M6P-BAS2-□
18x24	Momentary	1C	M6P-CMS1-□□	M6P-CMS1-□
		2C	M6P-CMS2-□□	M6P-CMS2-□
	Alternate	1C	M6P-CAS1-□□	M6P-CAS1-□
		2C	M6P-CAS2-□□	M6P-CAS2-□

• This list in only for solder / plug-in terminal type.
• This type No. of P.C board terminal type is as example below.

Example : M6P-AMS1 - 28 R → **M6P-AMS1 - R**

Solder/Plug-in Terminal

Example : M6P-AMP1 - 28 R → **M6P-AMP1 - R**

P.C board Terminal