

# Nieaf Instruments EazyVolt II 4-in-1 多功能相序電壓表

The EazyVolt II is a reliable and safe 4-in-1 automatic voltage tester up to 690 V, a resistance tester, a continuity tester and is able to indicate phase rotation by 2 poles.

Unique is the full LCD display with bargraph and backlight. The tester is integrated with a torch for testing in places with less lighting. The probe can be connected to the housing firmly.

## 特點：

- ◆ 具備電壓(6~690VAC/VDC)/斷路/電阻檢知功能(自動識別)
- ◆ 具備三相相序循環檢測系統(檢知相序是否同相位，無須相序表)
- ◆ 具單手操作金屬物活線識別警報功能
- ◆ 具夜間照明燈功能
- ◆ 具量測時 LCD 背光照明自動顯示功能
- ◆ 具量測時自動啟動/自動斷電功能
- ◆ 具備 IP64 防水防塵保護等級(IP65 申請中)



Specifications	
Voltage range	6- 690 Volt AC/DC
LED resolution	bargraph, 8.0 - 15.0V, res = 0,1V
	151 - 690V, res = 1V
Accuracy	±3% + 2d
Response time	< 0.1 s LED / < 0.5 s LCD
Resistance measurement	0 ... 2 kOhm (±3% + 10d)
Continuity	< 200 k Ohm
Frequency range	0 ... 65 Hz
Backlight	Including
Power supply	2x 1.5V LR03 batterij
IP-Protection	IP64/IP65 pending
Over voltage category	CATIII / 1000V - CAT IV / 600V
Standards	NEN EN 61010-1, EN 61243-3, EN 61557-7
Probe tips	2 mm. en 4 mm. with thread
Drop proof	1 meter
Test leads	1,2 meter
Dimensions	240 x 56 x 24 mm.
Weight	± 230 gram (incl. batteries)
Art.no.	626 000 610
Including	Manual and batteries

勝特力材料 886-3-5753170  
 勝特力电子(上海) 86-21-54151736  
 勝特力电子(深圳) 86-755-83298787  
[Http://www.100y.com.tw](http://www.100y.com.tw)