



勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-54151736
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

AC Axial Fan

Size=120X120X25 mm,Bearing System= SLEEVE bearing, Voltage=115VAC

| Model | P/N | Bearing | Rating Voltage (VAC) | Freq (HZ) | Power Current (AMP) | Power Consumption (WATTS) | Speed (RPM) | Air Flow (CFM) | Static Pressure (Inch-H2O) | Noise (dBA) | Weight (g) |
|---------|---------|------------------------------|----------------------|-----------|---------------------|---------------------------|-------------|----------------|----------------------------|-------------|------------|
| | | ● BALL ● VAPO ● SLEEVE | | | | | | | | | |
| SP101AT | 1122HSL | ● | 115 | 50/60 | 00.19/0.18 | 19/18 | 2000/2200 | 64/77 | 00.13/0.15 | 43/45 | 330 |
| SP101AT | 1122HST | ● | 115 | 50/60 | 00.19/0.18 | 19/18 | 2000/2200 | 64/77 | 00.13/0.15 | 43/45 | 330 |
| SP102AT | 1122MSL | ● | 115 | 50/60 | 00.13/0.12 | 14/13 | 1900/2000 | 54/64 | 00.13/0.13 | 42/43 | 330 |
| SP102AT | 1122MST | ● | 115 | 50/60 | 00.13/0.12 | 14/13 | 1900/2000 | 54/64 | 00.13/0.13 | 42/43 | 330 |
| SP103AT | 1122LSL | ● | 115 | 50/60 | 00.14/0.13 | 14/13 | 1600/1800 | 46/53 | 00.11/0.12 | 35/38 | 330 |
| SP103AT | 1122LST | ● | 115 | 50/60 | 00.14/0.13 | 14/13 | 1600/1800 | 46/53 | 00.11/0.12 | 35/38 | 330 |